

Protalk Door Intercom

Protalk Door Intercom

Tested with:

Gigaset T300/T500 PRO: Software version 4.6.5.0

Protalk Slim IPDP 01C: VoIP version: 1.58 UDV version: 6.0

Create SIP account in Gigaset T300/T500

Go to: Configuration - Phones - Add additional Telephones

Users	Details
Groups	Telephone Type: <input type="text" value="Standard Sip"/> Functionality: <input type="text" value="Phone"/>
Phones	Telephone name: <input type="text" value="Protalk.door"/> Password: <input type="text"/> <input type="button" value="Random password"/>
Modules	Server IP-Address: <input type="text" value="192.168.2.10"/> Last known Device-IP: 192.168.2.69
Voicemail	Extended Configuration
Conference	Options
Addressbook	nat: <input type="text" value="--choose--"/>
Phone numbers	Codecs: <input type="text" value="alaw,ulaw"/>
Lines	restr. to IP: <input type="text"/>

Use the settings like in the example above. Always use the Password generator to create a secure Password.

Configure the Protalk door intercom



Day mode

Menu:

- Network setting
- Basic parameters
- SIP parameters
- Setting audio
- Setting video
- Relays
- Time parameters
- Memory numbers
- User interface
- Service
- Video
- Help

Language:

english

SIP parameters:

SIP proxy server	Address:	<input type="text" value="192.168.2.10"/>
	Port:	<input type="text" value="5060"/>
SIP registrar server	Address:	<input type="text" value="192.168.2.10"/>
	Port:	<input type="text" value="5060"/>
Account module	Name:	<input type="text" value="Protalk.door"/>
	Password:	<input type="password" value="yHhKQeeuZJsdwCz"/>
	Auth. Id:	<input type="text" value="Protalk.door"/>
	Expiration [sec]:	<input type="text" value="600"/>

Registration successful

- Use (180 Ringing):**
- Use (183 Session progress):**
- Enable Simmetric RTP:**
- Send DTMF as SIP INFO:**
- Send DTMF according to RFC2833:**

SIP proxy server and **SIP registrar server** = IP address of the Gigaset T300/T500.

Account module Name and **Auth. ID** = Telephone name in Gigaset T300/T500.

Password = Password in Gigaset T300/T500.



Day mode

Menu:

- Network setting
- Basic parameters
- SIP parameters
- Setting audio
- Setting video
- Relays
- Time parameters
- Memory numbers
- User interface
- Service
- Video
- Help

Language:

english

Memory numbers:

	Group DAY	Group NIGHT
Button 1:	206	
Button 2:		
Button 3:		
Button 4:		
Button 5:		
Button 6:		
Button 7:		
Button 8:		
Button 9:		
Button 10:		
Button 11:		
Button 12:		
Button 13:		
Button 14:		
Button 15:		

Here you can define which number is dialled when the key is pressed, in this example number: 206.



Day mode

Menu:

- Network setting
- Basic parameters
- SIP parameters
- Setting audio
- Setting video
- Relays
- Time parameters
- Memory numbers
- User interface
- Service
- Video
- Help

Language:

english

Setting audio:

Priority 1:

Priority 2:

Priority 3:

Priority 4:

Please check if the correct codecs are enabled.

<ul style="list-style-type: none"> ▶ Network and Connections ▶ Telephony ▶ Messaging ▼ Services <ul style="list-style-type: none"> IP Info Services Internet Radio Door Interphone Online Directory 	<p>Door Interphone</p> <p>Enter name and SIP ID for Door interphone. Enter DTMF code for automatic door opener. Enter IP address of door camera (URL) and reload rate in ms (minimum: 200 ms).</p> <table border="1"> <thead> <tr> <th>Name</th> <th>SIP ID</th> <th>DTMF code</th> <th>Camera (URL)</th> <th>Reload Rate</th> </tr> </thead> <tbody> <tr> <td>Protalk</td> <td>205</td> <td>#2</td> <td>http://192.168.1</td> <td>500</td> </tr> </tbody> </table>	Name	SIP ID	DTMF code	Camera (URL)	Reload Rate	Protalk	205	#2	http://192.168.1	500
Name	SIP ID	DTMF code	Camera (URL)	Reload Rate							
Protalk	205	#2	http://192.168.1	500							

Web camera

Just add a Web camera with the door intercom URL (http://<IP address>/video.jpg)

Webcam	
Name of Webcam	IP adress of Webcam (URL)
Voordeur	<input type="text" value="http://192.168.178.69/video.j"/> <input type="button" value="Delete"/>

You can also use the web camera as screen-saver, under info service select the web camera you just added to the device.

Please select one info service for screensaver.	
<input type="radio"/> News	<input type="text"/>
<input type="radio"/> Weather	<input type="text"/>
<input checked="" type="radio"/> Webcam	<input type="text" value="Voordeur"/>



- [Protalk Door Intercom](#)
 - [Create SIP account in Gigaset T300/T500](#)
 - [Configure the Protalk door intercom](#)
 - [Gigaset User account.](#)
 - [Door intercom video integration Gigaset T300/T500](#)

- Door intercom video integration Gigaset DE700 and DE900.