

Interop Hybird 120 Gigaset Edition - Peoplefone

Peoplefone

| Feature | |
|---------------------|-----|
| Outgoing Calls | Yes |
| Incoming Calls | Yes |
| CLIP incoming | Yes |
| CLIP outgoing | Yes |
| Call Forwarding | Yes |
| Call Transfer | Yes |
| Call Waiting | Yes |
| DTMF | Yes |
| Anonymous Call | Yes |
| A-number forwarding | Yes |

- [Peoplefone](#)
 - [Hybird 120 Gigaset Edition settings.](#)
 - [Provider settings:](#)
 - [VoIP settings:](#)
 - [VoIP Menu](#)
 - [Advanced settings:](#)



Hybird 120 Gigaset Edition settings.

In the Hybird 120 Gigaset Edition go to "Assistants" - "PBX" and click on "New": --> add a new SIP Provider

- Save configuration
- Assistants
 - First steps
 - Internet Access
 - VPN
 - PBX
- System Management
- Physical Interfaces
- VoIP
- Numbering
- Terminals
- Call Routing
- Applications
- LAN
- Networking
- Multicast
- WAN
- VPN
- Firewall
- Local Services
- Maintenance
- External Reporting
- Monitoring

Trunks **Users**

View 20 per page << >> Go

| No. | Name | Connection Type | Ports | Status | | |
|-----|------------|--------------------|------------|--------|--|--|
| 01 | Peoplefone | SIP Provider (DDI) | Peoplefone | | | |

Page: 1, Items: 1 - 1

New

PBX - Connections Overview

These assistants guide you through all of the settings required set up and configure an analogue, ISDN or VoIP connection.

All of the configured connections are displayed in the overview. The following are listed: the **Name** of the connection, the **Connection Type** connection type (ISDN, ISDN (P-P), SIP provider, SIP provider (extension) of FXO), the **Ports** used (slot or provider name) and the current **Status**.

The relevant list field is deleted by pressing the button.

You can also edit existing entries with the aid of .

To add a connection, click **New**. Then follow the instructions. The list is called up again once the new connection has been configured, allowing you to set up other connections.

Copyright© Version 8.0, 2013 bintec elmeg GmbH

Provider settings:

Give the Line an unique name, insert the Registration user name and Password.

Save configuration

- Assistants
- First steps
- Internet Access
- VPN
- PBX
- System Management
- Physical Interfaces
- VoIP
- Numbering
- Terminals
- Call Routing
- Applications
- LAN
- Networking
- Multicast
- WAN
- VPN
- Firewall
- Local Services
- Maintenance
- External Reporting
- Monitoring

Trunks **Users**

Warning: Country code and/or City code not configured!

SIP Provider Settings

| | |
|------------------------------------|--------------------|
| Name | Peoplefone |
| Access Type | Direct Dial-In |
| Authentication ID | 90740928160 |
| Password | •••••••• |
| User Name | 90740928160 |
| Registrar | app1.peoplefone.ch |
| Trunk Numbers | |
| Base Number | 091252 |
| Class of Service | |
| Class of Service | Class of Service |
| Class of Service | CoS Default |
| <input type="button" value="Add"/> | |

Advanced Settings

PBX - Configuring an SIP provider (extension)

Enter the required data for a "VoIP dial-in with extension" scenario.

Name:

Enter a description for the connection to improve recognition.

Access Type:

DDI is entered here from your previous selection.

Authentication ID:

Enter your provider's authentication ID. A 64 digit alpha-numeric sequence is possible.

Password:

At this point, you can assign a password. A 32 digit alpha-numeric sequence is possible.

User Name:

Enter the user name you received from your VoIP provider. A 64 digit alpha-numeric sequence is possible.

Registrar:

Enter the DNS name or IP address of the SIP server. A 26 digit alpha-numeric sequence is possible.

Base Number:

Just add the telephone numbers for this SIP trunk in the "Advanced Settings"

Advanced Settings

| Registrar | | | | | | | | | | | | | | | | |
|-------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------|----------------|--|-----------------------------------|-----------------------------------------|--|-----------------------------------|-----------------------------------------|--|-----------------------------------|-----------------------------------------|--|------------------------------------|--|--|
| Registrar Port | <input type="text" value="5060"/> | | | | | | | | | | | | | | | |
| Transport Protocol | <input checked="" type="radio"/> UDP <input type="radio"/> TCP | | | | | | | | | | | | | | | |
| STUN server | | | | | | | | | | | | | | | | |
| STUN server | <input type="text"/> | | | | | | | | | | | | | | | |
| Port STUN server | <input type="text" value="3478"/> | | | | | | | | | | | | | | | |
| Trunk Numbers | | | | | | | | | | | | | | | | |
| P-P DDI Exception | <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="width: 40%;">P-P DDI Exception</th> <th style="width: 40%;">Displayed Name</th> <th style="width: 20%;"></th> </tr> </thead> <tbody> <tr> <td><input type="text" value="0570"/></td> <td><input type="text" value="0912520570"/></td> <td style="text-align: center;"></td> </tr> <tr> <td><input type="text" value="0571"/></td> <td><input type="text" value="0912520571"/></td> <td style="text-align: center;"></td> </tr> <tr> <td><input type="text" value="0572"/></td> <td><input type="text" value="0912520572"/></td> <td style="text-align: center;"></td> </tr> <tr> <td colspan="3" style="text-align: center;"><input type="button" value="Add"/></td> </tr> </tbody> </table> | P-P DDI Exception | Displayed Name | | <input type="text" value="0570"/> | <input type="text" value="0912520570"/> | | <input type="text" value="0571"/> | <input type="text" value="0912520571"/> | | <input type="text" value="0572"/> | <input type="text" value="0912520572"/> | | <input type="button" value="Add"/> | | |
| | P-P DDI Exception | Displayed Name | | | | | | | | | | | | | | |
| | <input type="text" value="0570"/> | <input type="text" value="0912520570"/> | | | | | | | | | | | | | | |
| | <input type="text" value="0571"/> | <input type="text" value="0912520571"/> | | | | | | | | | | | | | | |
| | <input type="text" value="0572"/> | <input type="text" value="0912520572"/> | | | | | | | | | | | | | | |
| <input type="button" value="Add"/> | | | | | | | | | | | | | | | | |
| Further Settings | | | | | | | | | | | | | | | | |
| Generate international phone number | <input type="checkbox"/> Enabled | | | | | | | | | | | | | | | |
| Generate national subscriber number | <input type="checkbox"/> Enabled | | | | | | | | | | | | | | | |
| <input type="button" value="OK"/> <input type="button" value="Cancel"/> | | | | | | | | | | | | | | | | |

VoIP settings:

Here you can define how the outgoing lines have to look like (e.g. Clip no Screening)

Save configuration

SIP Provider **Locations** **Codec Profiles** **Options**

| Basic Settings | |
|-------------------------------------------------------------------------|----------------------------------------------------------------------------------------|
| Description | Peoplefone |
| Provider Status | <input checked="" type="radio"/> Active <input type="radio"/> Inactive |
| Access Type | <input type="radio"/> Single Number(s) <input checked="" type="radio"/> Direct Dial-In |
| Authentication ID | 90740928160 |
| Password | •••••••• |
| User Name | 90740928160 |
| Domain | |
| Outgoing Signalling Settings | |
| Outgoing Signalling | Individual CLIP no Screening Number ▾ |
| Signal remote caller number | <input checked="" type="checkbox"/> Enabled |
| Registrar | |
| Registrar | app1.peoplefone.ch |
| Registrar Port | 5060 |
| Transport Protocol | <input checked="" type="radio"/> UDP <input type="radio"/> TCP |
| STUN | |
| STUN server | |
| Port STUN server | 3478 |
| Timer | |
| Registration Timer | 60 Seconds |
| Advanced Settings | |
| <input type="button" value="OK"/> <input type="button" value="Cancel"/> | |

VoIP Menu Advanced settings:

Please choose here the below settings when you use the CLIP No Screening.

Advanced Settings

| | |
|-----------------------------------------------|----------------------------------------------------------------------------------------------------------|
| Proxy | <input type="text"/> |
| Proxy Port | <input type="text" value="5060"/> |
| Transport Protocol | <input checked="" type="radio"/> UDP <input type="radio"/> TCP |
| Further Settings | |
| From Domain | <input type="text"/> |
| Number of allowed simultaneous Calls | <input type="text" value="No Limitation"/> ▾ |
| Location | <input type="text" value="Any Location"/> ▾ |
| Codec Profiles | <input type="text" value="System Default"/> ▾ |
| Dial End Monitoring Time | <input type="text" value="5"/> Seconds |
| Call Hold inside the PBX system | <input checked="" type="checkbox"/> Enabled |
| Call Forwarding extern (SIP 302) | <input type="checkbox"/> Enabled |
| Generate international phone number | <input type="checkbox"/> Enabled |
| Generate national subscriber number | <input type="checkbox"/> Enabled |
| Deactivate number suppression | <input type="checkbox"/> Enabled |
| SIP Header Field for User Name | <input type="radio"/> P-Preferred <input type="radio"/> P-Asserted <input checked="" type="radio"/> None |
| SIP Header Field(s) for Caller Address | <input type="checkbox"/> Display |
| | <input checked="" type="checkbox"/> User Name |
| | <input type="checkbox"/> P-Preferred |
| | <input type="checkbox"/> P-Asserted |
| Substitution of International Prefix with "+" | <input type="checkbox"/> Enabled |
| PBX coupling | <input type="checkbox"/> Enabled |
| Delete SIP bindings after Restart | <input checked="" type="checkbox"/> Enabled |
| Upstreaming Device with NAT | <input type="checkbox"/> Enabled |
| Early media support | <input checked="" type="checkbox"/> Enabled |
| Provider without Registration | <input type="checkbox"/> Enabled |