

# FAQ Expansion Module: Provisioning Parameter

---

## General

The provisioning parameters of the Expansion Module are the same as used for Maxwell 3 Function keys.

The numbering of the Function Keys starts with **8**, nevertheless if the Main Device is a Maxwell 2, 3 or a Maxwell Basic.

For Maxwell 4 the numbering of function keys on the Expansion Module starts with **38**.

Example:

```
<param name="PhoneUI.Keys.FunctionKeys.8.DisplayName" value="Maxwell 3"/>
```

Expansion module 1 level 1: X = (Function key) 8 - 36

Expansion module 1 level 2: X = (Function key) 37 - 65

Expansion module 2 level 1: X = (Function key) 66 - 94

Expansion module 2 level 2: X = (Function key) 95 - 123

Expansion module 3 level 1: X = (Function key) 124 - 152

Expansion module 3 level 2: X = (Function key) 153 - 181



### Page Toggle

Please be aware that one Function Key per page is used to toggle the pages and **cannot** be provisioned.

You cannot use **22** and **52** (Module 1), **82** and **112** (Module 2) and **142** and **172** (Module 3) as Function Keys Identifier.

---

## Available Functions

The Expansion Module supports the configuration of the following key types:

- No function
- QuickDial
- BLF (Busy Lamp field)
- SIP URI
- DTMF
- Action URL
- SIP INFO
- FAC (Feature Access Code)

---

## Parameter set

General:

X: Function Key number

Type value: -1 (No Function), 3 (Quick Dial), 4 (BLF), 5 (SIP URI), 7 (DTMF), 8 (Action URL), 10 (FAC)

Color: 0 = red, 1 = yellow, 2 = green

Type: QuickDial

```
<param name="PhoneUI.Keys.FunctionKeys.X.Type" value="3" />
<param name="PhoneUI.Keys.FunctionKeys.X.DisplayName" value="Maxwell Basic" />
<param name="PhoneUI.Keys.FunctionKeys.X.Connection" value="0" />
<param name="PhoneUI.Keys.FunctionKeys.X.PhoneNumber" value="1234" />
<param name="PhoneUI.Keys.FunctionKeys.X.Color" value="1" />
```

Type: BLF

```
<param name="PhoneUI.Keys.FunctionKeys.X.Type" value="4" />
<param name="PhoneUI.Keys.FunctionKeys.X.DisplayName" value="Maxwell 3" />
<param name="PhoneUI.Keys.FunctionKeys.X.Connection" value="0" />
<param name="PhoneUI.Keys.FunctionKeys.X.PhoneNumber" value="5678" />
<param name="PhoneUI.Keys.FunctionKeys.X.CallPickupCode" value="*8#" />
<param name="PhoneUI.Keys.FunctionKeys.X.Color" value="1" />
```

Type: SIP URI

```
<param name="PhoneUI.Keys.FunctionKeys.X.Type" value="5" />
<param name="PhoneUI.Keys.FunctionKeys.X.DisplayName" value="Maxwell 10" />
<param name="PhoneUI.Keys.FunctionKeys.X.URL" value="Maxwell10@gigaset.com" />
<param name="PhoneUI.Keys.FunctionKeys.X.Color" value="2" />
```

Type: Action URL

```
<param name="PhoneUI.Keys.FunctionKeys.X.Type" value="8" />
<param name="PhoneUI.Keys.FunctionKeys.X.DisplayName" value="Upload" />
<param name="PhoneUI.Keys.FunctionKeys.X.URL" value="http://<server ip>/upload.htm" />
<param name="PhoneUI.Keys.FunctionKeys.X.Color" value="0" />
```

Type: DTMF

```
<param name="PhoneUI.Keys.FunctionKeys.X.Type" value="7" />
<param name="PhoneUI.Keys.FunctionKeys.X.DisplayName" value="DTMF *1234#" />
<param name="PhoneUI.Keys.FunctionKeys.X.DTMFCode" value="*1234#" />
<param name="PhoneUI.Keys.FunctionKeys.X.Color" value="0" />
```

Type: FAC

```
<param name="PhoneUI.Keys.FunctionKeys.X.Type" value="10" />
<param name="PhoneUI.Keys.FunctionKeys.X.DisplayName" value="FAC on/off" />
<param name="PhoneUI.Keys.FunctionKeys.X.EnableCode" value="*1234" />
<param name="PhoneUI.Keys.FunctionKeys.X.DisableCode" value="#1234" />
<param name="PhoneUI.Keys.FunctionKeys.X.Color" value="2" />
```