

# Interop Hybird 120 Gigaset Edition - Peoplefone

## Peoplefone

Feature	
Outgoing Calls	Yes
Incoming Calls	Yes
CLIP incoming	Yes
CLIP outgoing	Yes
Call Forwarding	Yes
Call Transfer	Yes
Call Waiting	Yes
DTMF	Yes
Anonymous Call	Yes
A-number forwarding	Yes

- [Peoplefone](#)
  - [Hybird 120 Gigaset Edition settings.](#)
    - [Provider settings:](#)
    - [VoIP settings:](#)
    - [VoIP Menu](#)
    - [Advanced settings:](#)



## Hybird 120 Gigaset Edition settings.

In the Hybird 120 Gigaset Edition go to "Assistants" - "PBX" and click on "New": --> add a new SIP Provider

hybird 120 Gigaset

Hybird\_120\_GE

Language

English

View

Standard

Online Help

Logout

Gigaset

Save configuration

Assistants

First steps

Internet Access

VPN

PBX

System Management

Physical Interfaces

VoIP

Numbering

Terminals

Call Routing

Applications

LAN

Networking

Multicast

WAN

VPN

Firewall

Local Services

Maintenance

External Reporting

Monitoring

Trunks

Users

View 20 per page

<<

>>

Go

No.	Name	Connection Type	Ports	Status		
01	Peoplefone	SIP Provider (DDI)	Peoplefone			

Page: 1, Items: 1 - 1

New

PBX - Connections Overview

These assistants guide you through all of the settings required set up and configure an analogue, ISDN or VoIP connection.

All of the configured connections are displayed in the overview. The following are listed: the **Name** of the connection, the **Connection Type** connection type (ISDN, ISDN (P-P), SIP provider, SIP provider (extension) of FXO), the **Ports** used (slot or provider name) and the current **Status**.

The relevant list field is deleted by pressing the button.

You can also edit existing entries with the aid of .



To add a connection, click **New**. Then follow the instructions. The list is called up again once the new connection has been configured, allowing you to set up other connections.

Copyright© Version 8.0, 2013 bintec elmeg GmbH

## Provider settings:

Give the Line an unique name, insert the Registration user name and Password.

hybird 120 Gigaset  
Hybird\_120\_GE

Language English  View Standard  Online Help Logout

Gigaset

Save configuration

Assistants

- First steps
- Internet Access
- VPN
- PBX

System Management

Physical Interfaces

VoIP



- Numbering
- Terminals
- Call Routing
- Applications
- LAN
- Networking
- Multicast
- WAN
- VPN
- Firewall
- Local Services
- Maintenance
- External Reporting
- Monitoring

Trunks

Users

Warning: Country code and/or City code not configured!

SIP Provider Settings

Name	Peoplefone
Access Type	Direct Dial-In
Authentication ID	90740928160
Password	.....
User Name	90740928160
Registrar	app1.peoplefone.ch
Trunk Numbers	
Base Number	091252
Class of Service	
Class of Service	<div>Class of Service</div> <div>CoS Default </div> <div></div> <div>Add</div>

Advanced Settings

OK Cancel

PBX - Configuring an SIP provider (extension)

Enter the required data for a "VoIP dial-in with extension" scenario.

**Name:**  
Enter a description for the connection to improve recognition.

**Access Type:**  
DDI is entered here from your previous selection.

**Authentication ID:**  
Enter your provider's authentication ID. A 64 digit alpha-numeric sequence is possible.

**Password:**  
At this point, you can assign a password. A 32 digit alpha-numeric sequence is possible.

**User Name:**  
Enter the user name you received from your VoIP provider. A 64 digit alpha-numeric sequence is possible.

**Registrar:**  
Enter the DNS name or IP address of the SIP server. A 26 digit alpha-numeric sequence is possible.

**Base Number:**

Just add the telephone numbers for this SIP trunk in the "Advanced Settings"

Advanced Settings

Registrar

Registrar Port

5060

Transport Protocol

☒ UDP
☐ TCP

STUN server

STUN server

Port STUN server

3478

Trunk Numbers

P-P DDI Exception

P-P DDI Exception	Displayed Name	
0570	0912520570	
0571	0912520571	
0572	0912520572	

Add

Further Settings

Generate international phone number

☐ Enabled

Generate national subscriber number

☐ Enabled

OK

Cancel

## VoIP settings:

Here you can define how the outgoing lines have to look like (e.g. Clip no Screening)

Save configuration

Assistants

System Management

Physical Interfaces

VoIP

Settings

Numbering

Terminals

Call Routing

Applications

LAN

Networking

Multicast

WAN

VPN

Firewall

Local Services

Maintenance

External Reporting

Monitoring

SIP Provider

Locations

Codec Profiles

Options

Basic Settings

Description

Peoplefone

Provider Status

☒ Active
☐ Inactive

Access Type

☐ Single Number(s)
☒ Direct Dial-In

Authentication ID

90740928160

Password

••••••••

User Name

90740928160

Domain

Outgoing Signalling Settings

Outgoing Signalling

Individual CLIP no Screening Number

Signal remote caller number

☒ Enabled

Registrar

Registrar

app1.peoplefone.ch

Registrar Port

5060

Transport Protocol

☒ UDP
☐ TCP

STUN

STUN server

Port STUN server

3478

Timer

Registration Timer

60

Seconds

Advanced Settings

OK

Cancel

## VoIP Menu Advanced settings:

Please choose here the below settings when you use the CLIP No Screening.

## Advanced Settings

Proxy	<input type="text"/>
Proxy Port	<input type="text" value="5060"/>
Transport Protocol	<input checked="" type="radio"/> UDP <input type="radio"/> TCP
Further Settings	
From Domain	<input type="text"/>
Number of allowed simultaneous Calls	<input type="text" value="No Limitation"/>
Location	<input type="text" value="Any Location"/>
Codec Profiles	<input type="text" value="System Default"/>
Dial End Monitoring Time	<input type="text" value="5"/> Seconds
Call Hold inside the PBX system	<input checked="" type="checkbox"/> Enabled
Call Forwarding extern (SIP 302)	<input type="checkbox"/> Enabled
Generate international phone number	<input type="checkbox"/> Enabled
Generate national subscriber number	<input type="checkbox"/> Enabled
Deactivate number suppression	<input type="checkbox"/> Enabled
SIP Header Field for User Name	<input type="radio"/> P-Preferred <input type="radio"/> P-Asserted <input checked="" type="radio"/> None
SIP Header Field(s) for Caller Address	<input type="checkbox"/> Display
	<input checked="" type="checkbox"/> User Name
	<input type="checkbox"/> P-Preferred
	<input type="checkbox"/> P-Asserted
Substitution of International Prefix with "+"	<input type="checkbox"/> Enabled
PBX coupling	<input type="checkbox"/> Enabled
Delete SIP bindings after Restart	<input checked="" type="checkbox"/> Enabled
Upstreaming Device with NAT	<input type="checkbox"/> Enabled
Early media support	<input checked="" type="checkbox"/> Enabled
Provider without Registration	<input type="checkbox"/> Enabled