

# Maxwell 10 Build 2.4.9

## Release Notes

### Release Date:

27.01.2017

### Version:

2.4.9

### Improvements

- Video performance and compatibility (Telephony and door intercom)
- Anonymous Settings
- Implementation of G.729
- Improved energy handling via backlight Management (Night Mode), configuration via WEB-UI

Additionally Broadsoft issues were fixed and the certification is now completed and approved by Broadsoft.

### Bugfixes

- Headset communication via PTT button (Bluetooth, USB, DHSG)
- Robin Door Intercom video now working
- Country code check while dialing
- "Call completed elsewhere" no longer in MISSED calls
- Many additional fixes

### Known Issues

Unify app "myPortal to go": "Off-hook" - signalisation is not working properly, please use the Version V2.2.129

### Information

Due to technical design, wireless LAN and Bluetooth Audio should not be used simultaneously

Download

Software versions	
Android	5.1.1
DVF9919	03.641a
Build number	80_1_2.4.9

## Firmware update




#### Important

Due to the fact, that Android-5.1 requires a lot of more memory than older Android versions we recommend to insert an [external SD-card](#), or plug in an USB-stick with minimum 2GB free memory space, at least during the upgrade phase!

There are 3 options to upgrade.

## Option 1: Two step Method using an SD-card or USB-memory-stick.

1. Plug in an SD-card or USB-stick with at least 2GB free memory (or enter an external SD card). Then start the Maxwell-10 WEB-UI and follow exactly the following 3 steps:
2. In the web-interface go to: *System - Firmware Update* page and check if the *Data server* field is (default) [profile.gigaset.net/device](http://profile.gigaset.net/device)



The screenshot shows a web interface with a 'Data server' label, a text input field containing 'profile.gigaset.net/device', and an 'Update firmware' button. Below the input field is a link that says '..set custom url here'.

3. Press "Save"
4. Press "Update firmware"

The update will be done in 2 steps.

1. Upgrade to new Jelly Bean software with USB drivers upgrade to support the USB memory extension.
2. Upgrade to Lollipop.

## Option 2: One step method using external SD-card.

1. Enter an [external SD-card](#) (or plug in an USB-stick).
2. Download the software via the "Download" button on this page.
3. Unpack the zip file. You will get a .txt file with the Open Source License text and an encrypted zip file which is your firmware image.
4. In the web-interface go to: *System - Firmware Update* page and select the above extracted zip file.




The screenshot shows a web interface with a 'User-defined firmware file' label, a text input field, a 'Bladeren...' button, and a 'Load' button.

5. Start the upgrade.

## Option 3: One step method without external SD-card.

1. Do a [factory reset](#) of the Maxwell 10 to free all memory for firmware update.
2. Download the software via the "Download" button on this page.
3. Unpack the zip file. You will get a .txt file with the Open Source License text and an encrypted zip file which is your firmware image.
4. In the web-interface go to: *System - Firmware Update* page and select the above extracted zip file.



The screenshot shows a web interface with a 'User-defined firmware file' label, a text input field, a 'Bladeren...' button, and a 'Load' button.

5. Start the upgrade.