

FAQ Maxwell - BLF colors

Introduction

Here we describe how you can change the Function key LED color behavior.

Web-Interface setting:

Valid for Maxwell

Basic	2	3	4
-------	---	---	---

LED colour

☒ Red

☐ Yellow

☐ Green

☐ Standard

Device	LED Color							
	Red / Yellow / Green				Standard - NEW -			
	Idle	Busy	Fail	Ringing	Idle	Busy	Fail	Ringing
Maxwell Basic	Has no BLF keys, but Expansion module can be used to have BLF keys.							
Maxwell 2	Off	On	Off	Blinking	Off	Red	Off	Red blinking
Maxwell 3	Off	On	Off	Blinking	Green	Red	Yellow	Red blinking
Maxwell 4	Off	On	Off	Blinking	Green	Red	Yellow	Red blinking
Maxwell Expansion module	Off	On	Off	Blinking	Green	Red	Yellow	Red blinking

Auto provisioning

Parameter name	Description
PhoneUI.Keys.FunctionKeys.X.Color	"0" -> Red "1" -> Green
Maxwell 2, 3 and 4: X = (Function key) 0 - 249	"2" -> Yellow "3" -> Standard This parameter is ignored by Maxwell 2 for the main-device keys. Only expansion module keys can be used with multi-color.
Example: <code><param name="PhoneUI.Keys.FunctionKeys.0.Color" value="0"/></code>	