Baudisch

Baudisch the SIP station is supported Gigaset PBX v5.2. Operating in a model with CP-CAM video module is possible. Both devices can be configured manually.

Important Note:

Gigaset only supports the commissioning of the SIP component of the station. Any additional questions for the assembly of the station, installation of relay or switch functions and further, or safety-relevant components is not answered by Gigaset Support (phone or e-mail). The m anufacturers documentation and firmware must be confirmed directly by Baudisch. For more information, please visit the manufacturer web site (see below) or the manufacturer's documentation.



Conceptual and preparation of Gigaset PBX

- The SIP station and CP-CAM are two independent IP terminals. Both devices require each a separate IP address and must be configured separately. ٠
 - The SIP station is configured in the Gigaset PBX as a SIP phone with the SIP profile 'Baudisch Door Station'.
 - The username is freely chosen, e.g. baudisch.sip
 - Please create a password automatically with the random-function of the PBX.
 - Also a DTMF sequence can be stored convenience feature to trigger a switching function (e.g. open the door).
- The CP-CAM is configured as a property of the SIP phone.
- The URL to the image of the CP-CAM is:

http:// <IP-address CP-CAM> / jpg / image.jpg

Konfiguration													
	Editieren												
Benutzer	Detaildaten Konfiguration der SIP Zugangsdaten												
Gruppen	Art des Endgerätes:	Baudisch SIP Doo V	Funktionalität:	Telefon	~								
Telefone	Telefonname:	baudisch.sip	Passwort:	Jj4aCT2ir15Uj	5n4	Zufallspasswort							
🖗 Module	Verwendete Servera	dresse: 192.168.32.133	Letzte bekannte	Geräte-IP: 192	2.168.32	.159							
Voicemail	Autoprovisionionung												
Konferenz	Autoprovisionierung												
Adressbuch	Letzte Provisionierur	ig: 01.01.1	970 00:00:00										
71 ² Rufnummern	Eismusse-Version												
ULeitungen	Telefoneinstellunger	überschreiben:											
A Routing	Telefonematenungen												
Server	NAT-	ausvählen V											
Auswertung	Codecs:	alawulaw											
Anlagen- verbund	IP-Beschränkung:												
Sicherheit	Türsprechstelle												
祭+ Erweiterte Einstellungen	🖲 Einschalten 🔾	Ausschalten											
	Kamera-URL: http	://192.168.32.158/jpg/im	verbind	lung testen									
	DTMF: 123	4											
	Konfiguration der Schaltfunktionen	URL zur CP-CAM sowi	e der DTMF Sequen	z für									
				Speichern	Übernei	Abbreche							
	-					Schließe							

- The SIP phone is now assigned to a dedicated user. This can be named as desired, e.g. First name: Door; Name: Entrance
 The telephone-numbers of the user also allow calls to this station. This must be unlocked separately in the station.
 By the user-assignment the doorstation get the right to make external calls.
 It is recommended for those users to deactivate the right "Phone Log".

Benutzer: Erdgeschos	s, Tür					
Daten Umleitung	Telefone Rufnummern	iFMC Tasten	Gruppen Rechte			
Angezeigte Rufnumme	Nummer unterdr. V	Primäres Telefon:	SIP/baudisch.sip	~		
Anklopfen:	V aktivieren	Ruhe:	Alatia		E	
 SIP/baudisch.sip 		Kurnummer	Kingert	AKUV	×	
		198		V		
					+	

blocked URL

- The Baudisch SIP intercom calls internal or external numbers when pressing the ringing-button.
 In general, the target should be a group (Group Strategy: Ring All), in the example with group number 199.
 All participants in this group of the Gigaset PBX are notified accordingly if the ringing-button on the Baudisch SIP doorstation is pressed.
 Note: The combination with a module 'Group with Waiting-queue' is currently not supported.

Gruppe: Samme	Iruf Türe			
Gruppendaten	Umleitung Rufnum	mern Personenzuordnu	ing	
Gruppenname:	Sammelruf Türe			
Klingelstrategie:	Ring All Group			
Gruppen ID:	0002	Passwort:	Zufallspasswort	
Chateinstellunger	100			
Chatgruppe:				

Gruppendaten Umleitung	Rufnummern	Personenzuordnung	
Primäre interne Rufnummer:	199	×	
Primäre externe Rufnummer:		34	
Rufnummer			
199			×

List	e der Gruppenmitglieder		0
_	Benutzer	Angemeldet	
=	1. Kirk, James T.	Z	×
_	2. Chekov, Pavel		×

Configuring SIP station

Important Note:

Please follow carefully the instructions of the manufacturer's documentation for setup. Please also note that you must save the setting changes separately on each page.

Configuration actions

Phone book

The settings of the phone book within the SIP station define the destination numbers within the Gigaset PBX which should be called if the ringing-button is pressed. There are various settings available here. Here is a simple standard scenario described.

The central call configures the behavior of the station when you press the ringing-symbol without the use of the arrow keys. Depending on the model of the SIP station, further configuration may be required.

- Central phone (display text)
 - Name: Idle-display on the bell display in three rows, for example Line 1: Gigaset Communications, line 2: Please ring the bell!
 Number: Destination number when you press the bell, in the example, the group number 199

 - ° DTMF code: 4-digit code to trigger a function
 - Incoming: Reject
 - Relay: On
 - Group ID: None

Zentralruf (Anzeigetexte)

	Name	Nummer	D	TMF	-Co	de					Ankommend		Abgehend		Relais		Gruppen-ID
<mark>116</mark>	Gigaset Com.	199	1	•	2	Ŧ	3.	-	4	Ŧ	Abweisen	•	Ansage An	•	An	•	Keine 🗸
	Herzlich Willkomm]															

blocked URL

VoIP settings

- CODECs
 - Codec 1: PCMA
 - Codec 2: PCMU
 - ° Codec 2-6: None
- SIP settings

 SIP Registration: [x] Yes
 SIP Server: <Gigaset-IP>

 - SIP server port: 5060
 SIP Domain: <Gigaset-IP>
 SIP outbound proxy server: [x] No

 - Use DNS SRV: [x] No
 SIP User ID: <SIP-Telefon-Name>
 - SIP authentication ID: <SIP-Telephone-Name>
 - SIP authentication PIN: <SIP-Telephone-Passwort>
 - Username: <SIP-Telephone-Name>

SIP Einstellungen

SIP Registrierung:	O Nein	Ja	
SIP Server:	192.168	3.32.133	(IP oder URI)
SIP Server Port:	5060	(Standard 50	60)
SIP Domain:	192.168	3.32.133	
SIP Server als Outbound Proxy:	Nein	🔘 Ja	
Benutze DNS SRV:	Nein	© Ja	
SIP Benutzer ID:	baudise	ch.sip	
SIP Authentifizierung ID:	baudise	ch.sip	
SIP Authentifizierung PIN:	•••••		
Benutzername:	baudise	ch.sip	(Optional, z.B. Max Mustermann)

blocked URL

- Advanced SIP Settings

 Send DTMF: RFC2833
 Support PRACK (RFC3262): [x] no

 - ^o Please leave the other values at their default settings
- System
 - Syslog Server IP: <Gigaset-IP> (please use only in case of support)
 SNTP Server: <Gigaset-IP>

 - Time zone: GMT +01:00
 - ° Clock adjust: [x] yes

Hardware settings

Please make the settings according to the manufacturer's instructions and the requirements on site.

Configuration of CP-CAM

Important Note:

Please follow carefully the instructions of the manufacturer's documentation for setup.

In combination with the Gigaset PBX, the CP-CAM must be operated with a fixed IP address - either by a fixed configuration in the device or via a static lease in the DHCP server.

Configuration actions

- Settings --> Camera
 - Mode: QVGA (320 x 240)
 - Number of frames per second (sensor): 15
 Displayed images (video): Each 2nd
 - Displayed images (video). Each zi

blocked URL blocked URL

• If necessary change other settings to your requirements.

If a password protection for the interrogation of the video image is configured, following URL instead of the default one (mentioned above):

<Username> http://: @ <Password> <IP-address CP-CAM> / jpg / image.jpg

Manufacturer's documentation

- Manufacturer's documentation is available on the Baudisch website : http://www.baudisch.de/downloads#anleitungen (password: SIP-hightech)
- Manufacturers package to download: available here!

Sample Images

Sample images for demonstration purposes

blocked URL blocked URL blocked URL Anzeige im Gigaset DE900 Telefon