FAQ 3CX - Auto-provisioning N870/N670 using fixed handset positioning.

Introduction

Here we describe how to provisioning an Gigaset N870/N670 behind an 3CX PBX.

N870 provisioning

We have a running 3CX system with configured users and you have added the provisioning template like described here: FAQ 3CX - Auto-provisioning templates

In this example we do not use IPUI provisioning but fixed handset positioning, a feature of software 2.16.2 or higher.

Add FXS/DECT	×
Select Brand	
Gigaset	Ŧ
Select model/device	
Gigaset N870	Ŧ
Mac Address	
Mac Address	
	OK Cancel
tensions: Assign up to 250 extensions to this device. gaset DECT N870 Test 2 ок Cancel	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ок Cancel General Extensions	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ok General Extensions FXS/DECT Details	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ox Cancel General Extensions FXS/DECT Details Enter name for Device	(Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ox Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ok Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Provisioning Method	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ox Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Provisioning Method Local LAN (in the office) Local LAN (in the office)	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ox Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Provisioning Method Local LAN (in the office) Provisioning Link: http://192.168.178.51:5000/provisioning/l6to21pmaa1n/7c	♥ Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 OK Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Provisioning Method Local LAN (in the office) Provisioning Link: http://192.168.178.51:5000/provisioning/l6to2ipmaa1n/70 Mac Address 7C2F80F68993	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ok Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 OK Provisioning Method Local LAN (in the office) Provisioning Link: http://192.168.178.51:5000/provisioning/l6to2ipmaa1n/7C Mac Address 7C2F80F68993 Evaluation to the office Select Interface	Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ox Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Provisioning Method Local LAN (in the office) Provisioning Link: http://192.168.178.51:5000/provisioning/l6to21pmaa1n/7c Mac Address 7C2F80F68993 Select Interface 192.168.178.51	Help C2F80F68993.xml
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 ok General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Gigaset DECT N870 Test 2 Provisioning Method Local LAN (in the office) Provisioning Link: http://192.168.178.51:5000/provisioning/l6to2ipmaa1n/7C Mac Address 7C2F80F68993 Select Interface 192.168.178.51	♥ Help
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 OK Cancel General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Provisioning Method Local LAN (in the office) Provisioning Link: http://192.168.178.51:5000/provisioning/l6to21pmaa1n/7c Mac Address 7C2F80F68993 Select Interface 192.168.178.51 Language Facility	Help The second
tensions: Assign up to 250 extensions to this device. igaset DECT N870 Test 2 OK General Extensions FXS/DECT Details Enter name for Device Gigaset DECT N870 Test 2 Provisioning Method Local LAN (in the office) Provisioning Link: http://192.168.178.51:5000/provisioning/l6to21pmaa1n/7C Mac Address 7C2F80F68993 Select Interface 192.168.178.51 Language English	Help ▼

Gigaset settings:

In the web-interface go to: Settings - System - Provisioning and configuration

Copy the Provisioning link from the 3CX web-interface into the N870 Provisioning server URL, press Set and click on Start auto configuration.

The device is configured via provisioning. (You will get error message but you can discard this. The error message comes because you send empty settings for handsets that are not used.)

	¢\$ SETTINGS	i STATUS		()
#	Network	>	Provisioning and configuration	
Ø	DECT Manager	>		
&	Base stations	>	Provisioning server 🔞	http://192.168.178.51:5000/r
	Provider or PBX profiles		Auto configuration file 📀	🖻 Browse
	Mobile devices	>		✤ Start auto configuration
s.	Telephony	>		Ø
	Online directories	>		
۲	Online services	>		
ŧ				
	Web configurator			
	Provisioning and configu			

Register the handsets manually to the N870.

(i) Info

When you make changes on the 3CX platform, the platform will not send a SIP notify to trigger provisioning. You need to start provisioning on the N870 via:

- Web-interfaceWait when the device connects during the night