

# Interop IP Devices 42com

**Gigaset**pro  
Network

Advanced  
Interop

## 42com

### About 42com

42com Telecommunication GmbH was founded 2002 in Berlin. A significant year in the development of the European telecommunication market that had just recently created a sensation by the initiation of the so-called "Telecom Package". The new laws for harmonization of electronic communications networks outlined new rules while lowering the entrance barriers for free providers and allowing open competition.

One of the obstacles that business newcomers must overcome is the acquisition of expensive management and accounting software. Brothers and executive partners Thomas and Alexander Reinig from Berlin were aware of this demand and developed software that offers all of the sought-after features. The management and accounting platform allows users to make, control, manage and analyze VoIP calls. No purchase of this software is required, and does not need to be installed on your own network. Instead, the required modules are available on a rental basis. 42com was already using cloud technology – long before this term became established. This innovative custom development for web-based telecommunications has become the foundation for a range of successful applications.

## Documentation and information:

Find [here](#) the support page  
See below for a list with supported features when using the Gigaset PRO IP Devices on the providers network.

## Supported Features



Feature	Maxwell 10	Maxwell 3	Maxwell 3 Basic	N720 IP	N510 IP
Software release:	2.6.32	2.16.6	2.16.6	108	243
Basic Call	Yes	Yes	Yes	Yes	Yes
Calling line (CLIP)	Yes	Yes	Yes	Yes	Yes
Connected line (COLP)	_1	_1	_1	_1	_1
Anonymous call	_2	_2	_2	_2	_2
Do Not Disturb	Yes	Yes	Yes	-	-
Message waiting	Yes	Yes	Yes	Yes	Yes
Call list/history	Yes	Yes	Yes	Yes	Yes
Voice mail deposit/retrieval	_1	_1	_1	_1	_1
Call waiting	Yes	Yes	Yes	Yes	Yes
Call Hold / Toggle	Yes	Yes	Yes	Yes	Yes
Call forward (CFU)	_2	_2	_2	_2	_2
Call forward (CFNR)	_2	_2	_2	_2	_2
Call forward (CFB)	_2	_2	_2	_2	_2
Call Transfer attended	Yes	Yes	Yes	Yes	Yes
Call Transfer early attended	Yes	Yes	Yes	Yes	Yes
Call Transfer unattended	Yes	Yes	Yes	-	-
Call completed elsewhere	Yes	Yes	Yes	Yes	Yes

DTMF (RFC2833)	Yes	Yes	Yes	Yes	Yes
Conference 3pty	Yes	Yes	Yes	-	Yes
BLF Busy / Idle indication	Yes	Yes	Yes <sup>3</sup>	-	-
Call pick-up direct	Yes	Yes	Yes	Yes	Yes
Call pick-up group	Yes	Yes	Yes	Yes	Yes
Call pick-up BLF	Yes	Yes	Yes <sup>3</sup>	-	-
Auto provisioning	Yes	Yes	Yes	Yes	Yes
<b>SIP Security</b>					
SIPS		_2	_2	-	-
SIP via TLS		Yes	Yes	-	-
SRTP		Yes	Yes	-	-

-	Not supported by device
.1	Not supported by the platform
.2	Platform feature via FAC
3	Via key extention module

code	feature
*31* number	Anonymous call to this number
*32* number	Toggle Code: Enables/Disabled anonymous call for the next call On or Off (Announcement)
*32	Toggle Code: Enables/Disable anonymous call for all calls On/Off (Announcement)
#32	Toggle Code: Enables/Disable anonymous call for all calls On/Off (Announcement)
*35	Toggle Code: Hotdesking to login/out on a device

*35*[int]	Toggle Code: Hotdesking to login/out on a device
*35*[int]*[pin]	Toggle Code: Hotdesking to login/out on a device
*100 / #100	Toggle Code: Login/off in waiting queue, dependent on your previous state.
*101 / #101	Login/off in all waiting queues.
*102 / #102	Change Waiting queue status for all queues to "break"
*103 / #103	Logoff from all waiting queues.
1233	Voicemail box of user
*8	Pick up first ringing
*8[extension number]	Directed pickup of [Extension]
*8[group number]	Group pickup
*96 / #96	Voicemail box of user
*[xx]	Toggle Code: To activate/deactivate the dial plan with number xx
1233 [vmbox-nr]	Listen to voicemail messages of voicemail box number [vmbox-nr]
*96 [vmbox-nr]	Listen to voicemail messages of voicemail box number [vmbox-nr]
#96 [vmbox-nr]	Listen to voicemail messages of voicemail box number [vmbox-nr]

## Auto provisioning

The Gigaset N510, N720, Maxwell 10, Maxwell 3 and Maxwell basic are released behind the Kwebbl platform including auto provisioning.




Go to Devices and click +Add and choose Gigaset pro:




**New device** Next Step

1 — 2 — 3

**STEP 1: Adding device and assigning to extension**

Brand \*





Select the desired certified Gigaset pro product:

Model \*



Maxwell 10



Maxwell 3



Maxwell Basic




N510 IP PRO




N720 IP PRO

Enable auto-provisioning by clicking on No switch to change to Yes:


Model \*




Maxwell 10



Maxwell 3



Maxwell Basic



N510 IP PRO



N720 IP PRO

**Provisioning** I want to use provisioning for this device:  No

Enter the device MAC address and ID:

**Provisioning** I want to use provisioning for this device:  Yes

MAC-address \*  MAC ID \*

To finalize, click on next at the top.

When all steps are taken, like adding users and so on, the device will now automatically be added to the Gigaset pro redirect server.

Connect or restart the device and the device will auto-provisioned.