

Auto provisioning: CONFIGFILE URL

Download config file direct from http server without Gigaset file structure.

When this parameter is configured, the device will direct download the (xml) configuration file from the http server. If not configured, the Gigaset File structure is needed. This parameter can be configured using:

- Auto provisioning
- Web-Interface (Desktop devices and N510)

This feature is available in:

- DE900/700 Software 02.00.09
- DE410/310 Software 02.00.06
- N720 Software 84
- N510 Software 199

Desktop devices

How to trigger the device to download the configfile.

- After restart of the device
- Sending check-sync SIP notify message
- After time.

(If you press the "Auto configuration" button in the web-interface then the Gigaset file structure is needed)

XML syntax:

```
<S_CONFIGFILE_URL class="string" value="provider URL/xml/<MAC address>.xml"/>
```

Tag Name	Value	Location in web-interface
S_CONFIGFILE_URL	max. 255 characters from (0-9,a-z,A-Z,-,.,); default is empty it must be complete/proper URL such as http://domain/path/filename.xml .	System -> Firmware Update -> Configuration file URL

Web-interface:

Settings - System - Firmware Update - Configuration file URL:

N720

XML syntax:

```
<SYMB_ITEM ID="BS_IP_Data.ucl_PHONE_SYSTEM" class="symb_item" value="5"/>
```

```
<SYMB_ITEM ID="BS_IP_Data.aucS_CONFIGFILE_URL[0]" class="string" value="http://...path to xml file..."/>
```

With this values IWU will download profile from aucS_CONFIGFILE_URL after every check-sync.

Tag Name	Value	Location in web-interface
----------	-------	---------------------------

BS_IP_Data. aucS_CONFIGFILE_URL[0]	max. 255 characters from (0-9,a-z,A-Z,-,.); default is empty it must be complete/proper URL such as http://domain/path/filename.xml .	Not available.
---------------------------------------	--	----------------

x. 255 characters from (0-9,a-z,A-Z,-,.); default is empty it must be complete/proper URL such as http://domain/path/filename.xml .	System -> Firmware Update -> Configuration file URL
--	--

N510

XML syntax:

```
<S_CONFIGFILE_URL class="string" value="provider URL/xml/<MAC address>.xml"/>
```

Please take care that extra ' ' are used.

Tag Name	Value	Location in web-interface
S_CONFIGFILE_URL	max. 74 characters from (0-9,a-z,A-Z,-,.); default is empty it must be complete/proper URL such as http://domain/path/filename.xml .	Settings -> Management -> Firmware Update -> Configuration file URL

Web-interface:

Settings - Management - Firmware Update - Configuration file URL:

The screenshot shows the 'Firmware Update' settings page. The 'Configuration file (URL)' field is highlighted in red. The 'Data server' field contains the URL 'http://192.168.178.120/eg_prov/'. The 'Automatic check for software updates' section has radio buttons for 'Yes' and 'No', with 'Yes' selected. A descriptive text block explains the update process, and an 'Update firmware' button is at the bottom.

- Download config file direct from <http> server without Gigaset file structure.
- Desktop devices
 - XML syntax:
 - Web-interface:
- N720
 - XML syntax:
- N510
 - XML syntax:
 - Web-interface: