

FAQ SL800H / S700H / R700H - Ringtones

Introduction

The following ringtones are by default delivered with these handsets.

Ringtones
01 Signal
02 Memo (Msg prio medium from SW11)
03 Down (Internal calls)
04 Vibe (Emergency)
05 Egg
06 Gigaset (External calls)
07 Super 4
08 Set (Msg prio low from SW11)
09 Tone One (Group calls)
10 Step to B (Optional)
11 Sim
12 P Cut
13 T Cup
14 Piano
15 Dunken
16 Evolve
17 Autumn
18 Twelve
19 Smile (Door station))
20 Flightzone
21 Waste
22 Green Tea
23 Try Better
24 Carousel
25 Classic Ring
26 Fountain
27 Alarm 1 (msg prio high)
28 Alarm 2
29 Alarm 3
30 Alarm 4
31 Alarm 5
32 Alarm 6
33 Doorbell
34 DR1
35 DR2 (msg prio low changed with SW11)
36 DR3 (msg prio medium changed with SW11)
37 DR4
38 DR5

The Line ID is needed when you want provisioning the ringtones.

Distinctive ring	Line ID before SW 2.26	Line ID with SW 2.26 or higher	Default ringtones
Internal	internal	internal	Down
External	external	0x01	Gigaset
Group	N.A.	0x02	Tone One
Door	N.A.	0x03	smile
Emergency	N.A.	0x04	Vibe
Optional	N.A.	0x05	Step to B
Msg prio low	N.A.	0x09	DR2 -> changed to 8 Set in SW11
Msg prio medium	N.A.	0x10	DR3 -> changed to 02 Memo in SW11
Msg prio high	N.A.	0x11	Alarm1

Auto-provisioning

In the following example we have created an ringtone named **audiofile.722** using the external tool.

In the provisioning file we first upload the audio file before we assign it to the internal melody, else the assignment will not work if the audio file is not in the handset.

Dependent on the [distinctive ring](#) setting in the Nx70 the ringtone for the External line has to be configured using **external_calls_ringer_melody** or **ringer_melody_line_1** when we configured both then the setting distinctive ring has no influence, it will both work.

```
<?xml version="1.0" encoding="UTF-8"?>
<provisioning version="1.1" productID="Gsdecthx">

  <resources>

    <resource_file type="sounds" crc="0xFFFF" url="http://192.168.178.201/dbb/audiofile.722" />

    <!-- crc is not used -->

  </resources>

  <nvm>

    <param name="internal_calls_ringer_melody" value="audiofile" />
    <param name="external_calls_ringer_melody" value="07 Super 4" />
    <param name="ringer_melody_line_1" value="07 Super 4" />

    <!-- line_ID number can be found in the table above -->

  </nvm>

</provisioning>
```