

FAQ SL800H / S700H / R700H - Auto provisioning: Emergency Numbers

Introduction

You can enter up to three phone numbers as emergency numbers - that you can also dial when the keypad lock is PIN-protected.

Open handset **menu - Settings - Telephony - Emergency Numbers**

Via auto-provisioning (Handset software release 11 or higher) you can configure the Emergency numbers.

- Name
- Phone number

When using this feature, the existing entries are overwritten.



You can delete the Emergency list by sending an empty list.

Example

```
<?xml version="1.0" encoding="UTF-8"?>
<provisioning version="1.1" productID="Gsdecthx">
  <nvm>
    </nvm>
    <lists>
      <list list_name="emergency_dial">
        <entry name="Emer1" phone="1234567890"/>
        <entry name="Emer2" phone="112"/>
        <entry name="Emer3" phone="110"/>
      </list>
    </lists>
  </provisioning>
```