

FAQ SL800H / S700H / R700H - Auto provisioning: Create template using excel tool

Introduction

With this excel sheet, you can easily create an DECT handset (R700H/S700H/SL800H) provisioning template. This tool is optimized for the R700H/S700H and SL800H behind an Nx70 system, as the menu's/features in the handset are dependent on the system where it is connected.

[Download](#)

You need to enable the Macro's in excel as the creation of the provisioning files are done via Macro's.

- Option **"Full provisioning template"**
 - Enabled: Generate a Full template with all parameters
 - Disabled: Generate a template with only the settings that are changed (delta)
- Option **"Include always"** per parameter to make sure this parameter is added always, also when an delta provisioning file is generated
- Option **"Comments in provisioning file"** to add comments to the provisioning template
- Via the button **"Create Provisioning File"** the provisioning file is visible:
 - Excel sheet **"Provisioning_Template"**
 - Stored on your PC or on a share if **"File save to"** is enabled
- Via the button **"Reset to default"** change all settings back to default

Version	Changes
2.1	<ul style="list-style-type: none">• Load and Save provisioning file• Add Emergency numbers• Add Phonebook• Change color if value is changed• Fixed bugs
1.0	First version

Create an Full provisioning file or an file with:
- Changed parameters and
- Parameters "Include always" enabled

Add comments to the provisioning file, Yes/No

If enabled save the provisioning file on your PC.
You can change the location where to store the provisioning file.

Reset to all handset default settings to start from scratch

Create the provisioning file

Menu level 1	Visible	Menu level 2	Visible	Menu level 3	Visible	Menu level 4	Visible	Menu level 5	value	Include
Full provisioning template	<input checked="" type="checkbox"/>	Comments in prov. file	<input checked="" type="checkbox"/>	File save to: Z:\dbb\prov.xml	<input type="checkbox"/>	Reset to default	<input type="button" value="Reset to default"/>	Create Provisioning File	<input type="button" value="Create Provisioning File"/>	always
Additional Features	<input checked="" type="checkbox"/>	LED Torch (R700H)	<input checked="" type="checkbox"/>						TRUE	<input type="checkbox"/>
		One-Touch Call	<input checked="" type="checkbox"/>						TRUE	<input type="checkbox"/>
		Resource Directory	<input checked="" type="checkbox"/>						TRUE	<input type="checkbox"/>
		eMail	<input checked="" type="checkbox"/>						TRUE	<input type="checkbox"/>
Messaging	<input checked="" type="checkbox"/>								TRUE	<input type="checkbox"/>
Organizer	<input checked="" type="checkbox"/>								TRUE	<input type="checkbox"/>
		Calendar	<input checked="" type="checkbox"/>						TRUE	<input type="checkbox"/>
		Timer	<input checked="" type="checkbox"/>						TRUE	<input type="checkbox"/>
		Alarm Clock	<input checked="" type="checkbox"/>						TRUE	<input type="checkbox"/>
		Activation Time (alarm)							0	<input type="checkbox"/>
									0000	<input type="checkbox"/>

Option to hide or show the handset menu

Contains the provisioning parameter values.
- Greyed out are the Visible Yes/No, change via the selection option behind every menu item.
- The other values can be selected via a pull-down menu

Option to include this parameter always in the provisioning file