

Robin Compact SIP Door Intercom

Robin Compact SIP Door Intercom

Tested with: Gigaset T300/T500 PRO: Software version 4.6.5.0

Robin Compact SIP: Software version 2.0.1, Software build 1307, Build type Release

Create SIP account in Gigaset T300/T500

Goto: Configuration - Phones - Add additional Telephones

The screenshot shows a web interface for configuring a phone. On the left is a sidebar menu with options: Users, Groups, Phones (selected), Modules, Voicemail, Conference, Addressbook, Phone numbers, and Lines. The main area is titled 'Configuration' and 'Edit'. It has a 'Details' tab selected. The 'Details' section contains the following fields: Telephone Type (Standard Sip), Functionality (Phone), Telephone name (Robin.intercom), Password (<SIP Password>), Server IP-Address (192.168.2.10), and Last known Device-IP (empty). Below this is an 'Extended Configuration' section with an 'Options' tab. The 'Options' section contains: nat (choose...), Codecs (alaw, ulaw), and restr. to IP (empty).

Use the settings like in the example above.

Configure the Robin Compact SIP door intercom web-interface

The screenshot shows the top of the configuration interface with three tabs: Basic (selected), Advanced, and Tools. Below the tabs is a horizontal menu with options: Status, Device, Network, Phone book, Telephony (selected), Date/time, Door opener, and Call log.

Enter the SIP username and password as defined in the Gigaset T300/T500.

The SIP domain and proxy is the IP address of the Gigaset T300/T500.

The screenshot shows the 'SIP registration' configuration page. It has a blue header bar with the text 'SIP registration'. Below the header are several fields: SIP username (Robin.intercom), SIP password (masked with dots), SIP domain (192.168.2.10), SIP proxy (192.168.2.10), Register (enabled with a dropdown arrow and a question mark icon), and Registration expire time (1800 seconds). At the bottom, there are three tabs: Basic (selected), Advanced, and Tools. Below the tabs is a horizontal menu with options: Status, Device, Network, Phone book, Telephony, Date/time (selected), Door opener, and Call log.

Time server: Enter the IP address of the Gigaset T300/T500

Date and time configuration

Timezone : Amsterdam

Use time server : enabled

Time server : 192.168.2.10

Basic Advanced Tools

Status Device Network Phone book Telephony Date/time Door opener Call log

Here you can enter the number to be dialled when the door intercom key is pressed. In this example the number 130 is called.

Phone book

	Name	Number	Timeout	Connection timeout	
0	name	sip:130@192.168.2.10	☐	10	

Basic Advanced Tools

Status Device Network Phone book Telephony Date/time Door opener Call log

Here you can define which Phone book entry is used when the key is pressed.

Options

Default phone book entry : name

Secondary phone book entry : Not set

Third phone book entry : Not set

Auto-answer incoming calls : enabled

Basic Advanced Tools

Device info Status Network Password Telephony Schedule Audio RelaisK2 Upgrade System log

Please check if the correct codecs are enabled.

Audio codec support

codec prio	codec
Codec prio 1	alaw
Codec prio 2	none
Codec prio 3	none

Door opener activation.

To open the door, the following default codes are tested with the Gigaset T300/T500

Door opener activation

To open : ##

To keep open : 90

To close : 91

Gigaset User account.

Without a Gigaset user account, the door intercom can be used to dial an internal number. Incoming and Outgoing calls are not possible.

Incoming calls to the door intercom are only possible when the door intercom is assigned to a user.

In the Gigaset T300/T500 Goto: Configuration - Users and create a new user, only to be used for the door intercom (user license)

Configuration ✕

	User: Eric Baremans		
Users	User Data	Redirect	Phones
Groups	Phone Numbers		
Phones	Group Membership		
Modules	Rights		
Voicemail			

Primary Phone: SIP/Robin.intercom Call Waiting Indication: ☐ activate ?

Telephone	Ringing Number	Active	
▶ SIP/Robin.intercom		☒	✕



- Robin Compact SIP Door Intercom
 - [Create SIP account in Gigaset T300/T500](#)
 - [Configure the Robin Compact SIP door intercom web-interface](#)
 - [Gigaset User account.](#)