

FAQ T640 T440 Firmware upgrade devices

Introduction

The T640/T440 can automatically upgrade the Gigaset devices connected to the system via Auto provisioning.

T640/T440 settings

- Go to: **Administration - System - System Settings - Provisioning**

- Enable the Firmware update for the required devices.
 - Corded (DE310/410/700/900)
 - N510
 - N720
 - Maxwell 10
 - Maxwell 3
 - Maxwell basic
- Add the firmware files to the system in the directory: **/opt/galilei/htdocs/prov/gigaset/fwbin** using a file transfer program (winscp), with the correct naming:
 - de310-firmware version.img, example: de310-02.00.11.img
 - de410-firmware version.img, example: de410-02.00.11.img
 - de700-firmware version.img, example: de700-02.00.15.img
 - de900-firmware version.img, example: de900-02.00.15.img
 - merkur-firmware version.bin, example: merkur-42.192.bin
 - n720-mgr-firmware version.bin, example: n720-mgr-70.089.bin
 - n720-sat-firmware version.bin, example: n720-sat-70.089.bin
 - maxwell10-firmware version_enc.zip, example: maxwell10-1.0.40_enc.zip
 - GC_MAX_firmware version.bin, example: GC_MAX_1.11.6.bin

DE900/700/410/310

When the desktop device comes online, the T640/T440 will automatically start the upgrade via tftp. (Default setting)

After the upgrade, the normal provisioning procedure will start with the configuration files.

- [Introduction](#)
- [T640/T440 settings](#)
- [DE900/700/410/310](#)