FAQ Broadsoft Call Center Maxwell 10

Introduction

The BroadWorks® Call Center application delivers a comprehensive cloud solution with the advanced functionality required for a broad range of call centers. The Maxwell 10 can be used as an Call Center device with the possibility to Login/out or change the Agent status via integrated function keys.

Broadsoft example configuration.

User Call-Center license

In Broadsoft assign the Call Center license to the user. Select the user - Profile - Assign services, add the Call-Center standard license.

BROADSOFT

Service Provider >gigaset >Users : Gigaset	610		
Options: Profile Incoming Calls Outdoing Calls Call Control	Assign Services Assign Services allows you to assign or unassign services and service OK Apply Cancel	e packs for a user. If a service or service pack is unassigned the	service data that has been filled out will be lost.
Calling Plans	Available Service Packs		User Service Packs
Client Applications Messavina Utilities	CallControl_Advance_V1 HEN_v1 Nobility_v1 Premium_v3 Trunk_v3	Add > Remove < Add All >> Remove All	Base_v1 Busines_v1 Premium_v1
	Available Services		User Services
	Advice Of Charge Alternate Numbers	Add >	Call Center - Standard

Call Center Profile

Under group policies go to Call Center - Call Centers - Click on Add Call Center wizard and create a callcenter like the example below.

BRMADSOFT

Service Provider >gigaset >Ca	an Centers : giga_standard
Options: Profile	Call Center Profile
Routing Policies	Modify the selected call center.
Calling Plans	OK Apply Delete Cancel
<u>Utilities</u>	
	Call Center Type: Standard Upgrade Call Center Type (Also saves current screen data)
	Call Center ID: giga_standard Change User ID (Also saves current screen data)
	* Name: giga_standard
	* Calling Line ID Last Name: Standard * Calling Line ID First Name: GIGA
	Department None Language:
	Time Zone: (GMT+01:00) Europe/Amsterdam 🔻 Network Class of Service: IntRiskNotAllowed 🔻
	Group Policy: 💿 Circular 💿 Regular 👁 Simultaneous 🛇 Uniform 🔍 Weighted Call Distribution
	Bandwidth and QoS Settings
	Preferred announcement / music codec for external calls: None
	Preferred announcement / music codec for internal calls: None •
	Call Center Settings
	Queue Length: 2 calls Enable video support
	✓ Play ringing when offering call ✓ Allow callers to dial 0 to escape out of queue
	Reset caller statistics upon entry to queue
	Reporting Settings
	Enable Call Center External Reporting
	Agent Settings
	✓ Allow agents to join Call Centers
	Allow Call Waiting on agents
	✓ Enable calls to agents in wrap-up state
	✓ Enable maximum ACD wrap-up timer: 01 :00 (minutes:seconds)
	Automatically set agent state to Wrap-Up 🔹 after call

Assign agents

Assign the agents to the Call Center group.

BREADSOFT

Service Provider >gigaset >Call Centers : g	iga_standard		
Options: Profile Routing Policies Calling Plans Utilities	Agents Configure the list of agents that belong to this call center. Users are available Center - Standard may be assigned to Basic or Standard call center. Users OK Apply Cancel Enter search criteria below User ID V Starts With V	vie if they have been assigned an appropriate Call Center feature. Use is with Call Center - Premum may be assigned to any call center.	ers with Call Center - Basic may be assigned to Basic call o
			,
	Available Agents		Assigned Agents
		Add > Remove <	(Gigaset3610)
	*	Add All >> Remove All	Move Up Move Down

Maxwell 10 configuration

In the web-interface of the Maxwell 10 go to: Settings - Network and Connections - Phone systems - Call Center Login ID

This Call Center Login ID is the same like in the Broadsoft menu: Call Center Profile - Call Center ID



Maxwell 10 Call Center keys.

In the Maxwell 10 you will now have 3 additional keys.

- Call Center
- Available
- Wrap up (When Available is ON)

-								₫₽ 🚺 14:05
1	5062							
	ANC	DNYMOUS	ON	CALL CE	ENTER	OFF	AVAILABLE	OFF
ѧвс↓	₹*	ţ						
				\leftarrow	\Box			

When you change the status on the device, you will see that also the status is changed on the Broadsoft platform.

	·				
Options: Profile Incoming Calls	Call Centers Call Centers displays your current ACD state and all the ACDs you belong to and permitted by your administrator.				
Outgoing Calls					
Call Control	ОК	Apply	Can	cel	
Calling Plans					
Client Applications	0.11.0.1			Diama diama di	
Messaging	Call Center Service Assigned: Standard				
Utilities		AC	D State:	Wrap-Up	•
	A	Agent Threshold Profile:		Sign-In Sign-Out	hreshold Profile 🔻
	Use Guard Timer Setting:		Available	er	
				Unavailable Wrap-Up	r for 5 ▼ seconds
	Use Agen	t Unavailable S	Settings:	Default	User

(i) Important

If you change it on the platform via the web-interface then the platform will not inform the device changes are made, therefore the device will not show the actual Call Center settings. If you always use the phone to change the settings, then the buttons will show the correct Call Center status.

- Introduction
- Introduction
 Broadsoft example configuration.

 User Call-Center license
 Call Center Profile
 Assign agents

 Maxwell 10 configuration
 Maxwell 10 Call Center keys.