

FAQ N510 Registration of Polycom DECT Soundstation



You can register other GAP conform DECT Portable Part on N510IP PRO with their own specific registration procedure.

To start the registration for other devices on a N510IP base station

- **press the Registration Button in front of base for approx. 3seconds**

or use the Web configurator of N510IP:

- **Settings -> Management -> Miscellaneous-> Start Registration**

The screenshot shows the web configurator interface for a Gigaset N510 IP PRO. The top navigation bar includes 'Home', 'Settings', and 'Status', with a 'Log Off' link on the right. A left sidebar lists various settings categories: Network, Telephony, Messaging, Directories, Management, Date & Time, Local Settings, Miscellaneous (highlighted in orange), Reboot & Reset, Save & Restore, and Firmware Update. The main content area is titled 'Register new handsets' and contains several options: 'Switch to handset registration mode:' with a 'Start Registration' button; 'Eco Mode' with a checkbox and description; 'Eco Mode+' with a checkbox and description; 'Change system PIN of base station' with a 'New PIN:' input field; 'LED signalling on base station'; 'Signal Ethernet Connection and Traffic:' with radio buttons for 'Yes' and 'No'; and 'VoIP Status' with a 'Show VoIP status on handset:' option and radio buttons for 'Yes' and 'No'. At the bottom right are 'Set' and 'Cancel' buttons.

Please note: All base connections are assigned to a Portable Part as receive connections directly after registration is complete. The first configured VoIP connection is assigned to the Portable Part as a send connection.

To find out The Registration procedures of other conforming DECT Portable Parts (PP) please look into their user manuals.

As an example the registration procedure of an conference phone (PP) POLYCOM Soundstation 2W

- Go to the menu and navigate to 'Admin Setup -> Diagnostics -> Restore Defaults' and press the 'OK' soft button. It will work instantaneously, then navigate down to 'Reboot Phone' and press the 'Reboot' soft button. Your phone will reboot.
- Go to the menu and navigate to 'Admin Setup -> Registration' and follow the steps carefully.

- choose the connection protocol **GAP** and press 'OK'