

Hybird - VoIP Unlimited

VoIP Unlimited

Feature	
Outgoing Calls	Yes
Incoming Calls	Yes
CLIP incoming	Yes
CLIP outgoing	Yes
Call Forwarding	Yes ¹
Call Transfer	Yes
Call Waiting	Yes
DTMF	Yes
Anonymous Call	No ²
A-number forwarding	-

1 - Call forwarding through system only, redirects via 302 are not supported by VoIP Unlimited

2 - Anonymous call is not supported, alternatively precede the number dialled with 141 and VoIP unlimited will withhold for you.



VoIP Unlimited provides services to small and medium businesses in partnership with ICT solution providers, system integrators, traditional telephony dealers, and others who supply VoIP services as part of their offering to customers. Our services include SIP trunks, broadband circuits, wideband Ethernet, and MPLS networks. We also provide CPS, WLR, and T38 compatible FoIP (Fax over IP).

- [VoIP Unlimited](#)
 - [Gigaset Hybird settings.](#)
 - [Assistants/PBX/Trunks](#)

Gigaset Hybird settings.

When configuring a SIP trunk into the Hybird you must complete the following settings:

1. Assistants/PBX/Trunks
-

Assistants/PBX/Trunks

1 - Create a New trunk

2 - Connection Type = SIP Provider (DDI)

3 - Sip Provider Settings

Name = Info only

Authentication ID = SIP-ID given to you from VoIP Unlimited

Password = Password given to you from VoIP Unlimited

Registrar = sip.voip-unlimited.net

4 - Trunk Numbers

Insert the range minus the last x digits.

For example if your range is 555500 to 555599,

Extensions = 10 to 20

Make the base number as 5555

555510 to 555520 will route direct to extensions, all other numbers would need to be added to P-P DDI Exception (see below)

5 - Class of Service - Select a COS

Advanced Settings

6 - Registrar Port

7 - Transport Protocol

8 - STUN server

If required : stun.voip-unlimited.net

Port = 10000

9 - P-P DDI Exceptions

Add any DDI's not going to extensions with the same number.

Just the last digits from the range, in the example above any DDI 00 to 99.

Select Voice connection type:	
Connection Type	SIP Provider (DDI) ▼

Warning: Country code and/or City code not configured!							
SIP Provider Settings							
Name	VoIP Unlimited						
Access Type	Direct Dial-In						
Authentication ID	SIP-ID						
Password	*****						
User Name	SIP-ID						
Registrar	sip.voip-unlimited.net						
Trunk Numbers							
Base Number	number range - last n digits						
Class of Service							
Class of Service	<table border="1"> <tr> <td>Class of Service</td> <td>CoS Default ▼</td> <td></td> </tr> <tr> <td colspan="3">Add</td> </tr> </table>	Class of Service	CoS Default ▼		Add		
Class of Service	CoS Default ▼						
Add							

Advanced Settings										
Registrar										
Registrar Port	5060									
Transport Protocol	<input checked="" type="radio"/> UDP <input type="radio"/> TCP									
STUN server										
STUN server										
Port STUN server	3478									
Trunk Numbers										
P-P DDI Exception	<table border="1"> <thead> <tr> <th>P-P DDI Exception</th> <th>Displayed Name</th> <th></th> </tr> </thead> <tbody> <tr> <td>55</td> <td>Main</td> <td></td> </tr> <tr> <td colspan="3">Add</td> </tr> </tbody> </table>	P-P DDI Exception	Displayed Name		55	Main		Add		
P-P DDI Exception	Displayed Name									
55	Main									
Add										
Further Settings										
Generate international phone number	<input type="checkbox"/> Enabled									
Generate national subscriber number	<input type="checkbox"/> Enabled									
<input type="button" value="OK"/> <input type="button" value="Cancel"/>										