

DExxx - Programmable Keys

Your Gigaset DE410 / DE700 / DE900 IP PRO allows you to assign frequently used functions or phone numbers to up to 14 keys so that you can access them with one key press. You can increase the number of function keys by connecting extension modules.

For DE310/410 IP PRO the keys of the dialpad (0-9) can be used as [speed-dial-keys](#).

Functionality:

Line

Assigns a specific connection (VoIP account) to the function key. You can use the key to make a call via this connection or to answer an incoming call for this connection. The key flashes if a call comes in and lights up if the line is busy.

Park + Orbit

This function key is used to "park" a call. The participant hears the hold music. This function key allows you to transfer calls within a group, which share a common line. It will be configured on all extensions for the group. The "Park + Orbit" keys on all extensions flash if a call has been "parked" on an extension. The call can be picked up on any extension by pressing the key. Enter the Phone Number of the shared line that is configured on the phone system as identifier.

Speed Dial

Assigns the speed dial for a phone number to the function key. Enter the phone number that is to be dialled using this function key.

BLF

A function key that is configured as BLF (Busy Lamp Field) indicates the status of a shared line. It will be configured on all extensions for the group. The keys will flash on all extensions if a call comes in and light up if the line on any extension is busy. No actions are possible for this key. Enter the Phone Number of the shared line that is configured on the phone system as identifier.

Call Divert

Assigns a call divert to the function key. Enter the connection for which you want the call divert to apply and enter the Phone Number to which the calls are to be diverted.

XML-Content (Not for DE410)

On a function key of this type, you can store a function that has been defined in a XML file.

DTMF

Assign a number to a function key that is dialled using DTMF

Menu - Next Call anonymous

Open the menu -> Select Services -> Next Call anonymous

Menu - Call Divert

Open the menu -> Select Services -> Call Divert

Menu - Resource Directory (Not for DE410)

Open the menu -> Additional Features -> Resource Directory

Menu - Internet Radio (Not for DE410)

Open the menu -> Additional Features -> Internet Radio

None

Question

If the device is connected to the Gigaset T300 / T500, and the user will logon using the code *77<login id>. Will the function keys also be provisioned?

Answer

No, the function keys will not be provisioned automatically. This because the Devices do not have self labelling keys. So if the keys will be auto provisioned, the paper labels do not match. The user can copy the keys, but should start this manually with one key press in the T300/T500 web-interface.



New sw-releases might have additional features and functions available for the programmable keys. Please refer to the sw-release-notes and the actual manuals.