Maxwell 10 Build 2.5.33.1

Release Notes

Release Date:

17.05.2017

Version:

2.5.33.1

Improvements

- Update of Android security patches
- Unify approved
- Incomming calls accumulated by callers
- Bigger and faster programmable key widget
- Enhanced ringtone settings external, internal and group ringtones selectable

Bugfixes

- Call transfer started if END key is pressed on Maxwell during consultation call
- · Missed call melody not turns off when call waiting is over
- Translation issues fixed
- elmeg IP 680 matters corrected
- Call list date correction
- Many additional issues were fixed

Information

Due to technical design, wireless LAN and Bluetooth Audio should not be used simultaneously

Download Software versions Android 5.1.1 DVF9919 03.641a Build number 80_1_2.5.33.1

Firmware update

Important

Due to the fact, that Android-5.1 requires a lot of more memory than older Android versions we recommend to insert an external SD-card, or plug in an USB-stick with minimum 2GB free memory space, at least during the upgrade phase!

There are 3 options to upgrade.

Option 1: Two step Method using an SD-card or USB-memory-stick.

 Plug in an SD-card or USB-stick with at least 2GB free memory (or enter an external SD card). Then start the Maxwell-10 WEB-UI (klick on the Web Server Address - shown in the Maxwell 10 under "Settings=>WebUI - log in (Standard Password is "admin") and follow exactly the following 3 steps: 2. In the web-interface go to: System - Firmware Update page and check if the Data server field is (default) profile.gigaset.net/device

profile.gigaset.net/device ..set custom url here Update firmware

Data server	

3. Press "Save"

4. Press "Update firmware"

The update will be done in 2 steps.

- 1. Upgrade to new Jelly Bean software with USB drivers upgrade to support the USB memory extension.
- 2. Upgrade to Lollipop.

Option 2: One step method using external SD-card.

- 1. Enter an external SD-card (or plug in an USB-stick).
- 2. Download the software via the "Download" button on this page.
- 3. Unpack the zip file. You will get a .txt file with the Open Source License text and an encrypted zip file which is your firmware image.

4.	In the web-interface go to: 3	System - Firmware	Update page and	d select the above	extracted zip file.
		-		Di i	

User-defined firmware file	Bladeren	Load

5. Start the upgrade.

Option 3: One step method without external SD-card.

- 1. Do a factory reset of the Maxwell 10 to free all memory for firmware update.
- 2. Download the software via the "Download" button on this page.
- 3. Unpack the zip file. You will get a .txt file with the Open Source License text and an encrypted zip file which is your firmware image.
- 4. In the web-interface go to: System Firmware Update page and select the above extracted zip file.

User-defined firmware file	Bladeren	Load

5. Start the upgrade.