

Interop T300/T500 Telfort

Telfort ISP

Feature	
Outgoing Calls	Yes
Incoming Calls	Yes
CLIP incoming	Yes
CLIP outgoing	Yes
Call Forwarding	Yes
Call Transfer	Yes
Call Waiting	Yes
DTMF	Yes
Anonymous Call	Yes
A-number forwarding	No



- [Telfort ISP](#)
 - [Gigaset T300/T500 settings.](#)
 - [Provider settings:](#)
 - [Number Area settings:](#)
 - [Extended settings:](#)

Gigaset T300/T500 settings.

In the Gigaset PBX go to "Configuration" - "Lines" - "Lines" and click on: **New Line**

Provider settings:

Give the Line an unique name, insert the Registration user name and Password.

<input checked="" type="checkbox"/>	<input type="text" value="Telfort"/>	No.: 4	Provider Connection
Provider:	<input type="text" value="Telfort"/>	Provider Status:	Registered
Authentication:	<input checked="" type="radio"/> yes <input type="radio"/> no		
User Name:	<input type="text" value="<Username>"/>		
Password:	<input type="password" value="....."/>		
Provider	Number Area	Extended	

In the Provider pull-down list, select "new.."

Configuratie

Gebruikers

Groepen

Telefoon

Modules

Voicemail

Conferentie

Telefoonboek

Telefoonnummer

Lijnen

Routing

Server

Analyse

Interconnectie

Beveiliging

Geavanceerde instellingen

Provider bewerken

Providernaam:

Telfort

Lijnprotocol

SIP

Lijnconfiguratie

type:

friend

host:

voip.telfortzakelijk.c

dtmfmode:

rfc2833

permit:

auth mode:

Username/Password

deny:

auth:

plaintext

canreinvite:

no

nat:

disallow:

all

allow:

alaw

Outbound Proxy:

insecure:

very

progressinband:

port:

5060

qualify:

no

defaultip:

rtptimeout:

rtholdtimeout:

mask:

fromdomain:

voip.telfortzakelijk.c

fromuser:

NummerWeergave:

Type:

custom

Formaat inkomend:

11 (222) XXX

Formaat uitgaand:

11 (222) XXX

Wissen

Opslaan

Annuleren

Sluiten

Number Area settings:

Just add the telephone numbers for this SIP trunk. The Country Code and Area Code can be filled in, if different than the default setting.

☒

Telfort

No.: 4

Provider Connection

Country Code:

Area Code:

478

Number Type	Number	Number Area
Single Number	0031(478) 759	ABC X
Single Number	0031(478) 759	ABC X

+

Provider

Number Area

Extended

Extended settings:

To enable incoming calls, you need to use the settings below.

Open the Manual Configuration and change the default settings like in the example below. Do not forget to enable the check-box Active.

<input checked="" type="checkbox"/>	Telfort	No.: 4	Provider Connection
Line Prefix: ** <input type="text"/> *			
Deposit: <input checked="" type="radio"/> Default <input type="radio"/> Internal Number: <input type="text"/>			
No Screening: <input type="checkbox"/> Phone Number Prefix: <input type="text" value="none"/>			
Max Connection: <input type="text" value="0"/>			
<div> <div>Manual Configuration</div> <div>Active: <input checked="" type="checkbox"/></div> <div></div> </div> <div> <pre> [Telfort-incoming] exten => _.,1,Set(channelname=Telfort-incoming) exten => _.,2,Set(lineconfigid=1748) exten => _.,3,Set(var_to=\${SIP_HEADER(To)}) exten => _.,4,Set(firstcut=\${CUT(var_to,:,2)}) exten => _.,5,Set(secoundcut=\${CUT(firstcut,@,1)}) exten => _.,6,Set(CALLERID(all)=\${CALLERID(number)}) exten => _.,7,Goto(Telfort-incoming-manuell,\${secoundcut},1) </pre> </div>			
<div> <div>Provider</div> <div>Number Area</div> <div>Extended</div> </div>			

You can copy the text below to paste into the field.

[Telfort-incoming]

```

exten => _.,1,Set(channelname=Telfort-incoming)
exten => _.,2,Set(lineconfigid=1748)
exten => _.,3,Set(var_to=${SIP_HEADER(To)})
exten => _.,4,Set(firstcut=${CUT(var_to,:,2)})
exten => _.,5,Set(secoundcut=${CUT(firstcut,@,1)})
exten => _.,6,Set(CALLERID(all)=${CALLERID(number)})
exten => _.,7,Goto(Telfort-incoming-manuell,${secoundcut},1)

```

[Telfort-incoming-manuell]

```

exten => _X.,1,Goto(incoming,${secoundcut},1)
exten => _+X.,1,Goto(incoming,${secoundcut},1)

```