

## FAQ - XHTML (RAP)

<b>Valid for:</b>	N610	N670	N870	N870E	Embedded Integrator	Virtual Integrator
-------------------	------	------	------	-------	---------------------	--------------------

## Introduction

The N870 is able to show XHTML pages.

You can create your own Application like an PBX Manager that the user could use to control his PBX functionality. Like:

- Voicemail
- Call Lists
- Phonebooks
- DND
- Login / Logoff
- Call Forwarding
- ...

In the N720 and N510 we called this feature RAP.

For more detailed information about the XHTML protocol, check this [wiki page](#).

## Web-interface

Open the N870 web-interface and go to: SETTINGS - Online services - XHTML

There are up to 4 XHTML services possible.

**Gigaset**
Gigaset N870 IP PRO

**SETTINGS**

- Network >
- DECT Manager >
- Base stations >
- Provider or PBX profiles >
- Mobile devices >
- Telephony >
- Online directories >
- Online services ▾
- XHTML
- System >

i STATUS
? Help ↗ Logout

### XHTML

#	Name	Server url
1	<input type="text"/>	
2	<input type="text"/>	
3	<input type="text"/>	
4	<input type="text"/>	

**Global settings**

Add SIP-ID ☐ Yes ☒ No

---

#### XHTML 1

☐ Activate

☐ Yes ☒ No

Parameter	Auto-provisioning parameter	Description
Activate	RapService.< 3-6>.Activated	Enabled or Disable the selected XHTML service
Name for menu	RapService.< 3-6>.Name	Name visible in the handset menu when selecting this service
Softkey name Not available in Web-interface, will come.	RapService.< 3-6>.SoftkeyName	Name of the softkey, this is limited to 8 characters
Server address	RapService.< 3-6>.ServerURL	The URL of the XHTML service
Use SIP credentials	RapService.< 3-6>.UseSIP	In case of authentication is needed, you can use the SIP credentials or enter your own credentials.
Username	RapService.< 3-6>.Username	
Password	RapService.< 3-6>.Password	
Add SIP-ID	DmGlobal.0.AddSipld	Add the SIPID in the HTTP get request to identify the handset/account.



If "Use SIP credentials" is set to "No" then a username and/or password should be inserted as else system does not try to query server.

## Auto-provisioning

Here is an auto provisioning example:

```
<?xml version="1.0" encoding="UTF-8"?>
<gigaset>
  <provisioning version="1.1" productID="e2">
    <nvm>
      <param name="RapService.3.Activated" value="1"/>
      <param name="RapService.3.Name" value="PBX Manager"/>
      <param name="RapService.3.ServerURL" value="http://192.168.178.200/xhtml1"/>
      <param name="RapService.3.SoftkeyName" value="PBX"/>
      <param name="RapService.3.UseSIP" value="1"/>
      <param name="DmGlobal.0.AddSipld" value="1"/>
    </nvm>
  </provisioning>
</gigaset>
```