FAQ - Auto provisioning: Nested profiles

Valid for:	N610	N670	N870	N870E	Embedded Integrator	Virtual Integrator

Valid for N610 / N670 / N870 / N870E.

In some situations you would like to have the possibility to load multiple provisioning files.

- First file with general settings
- Second file with device specific settings
- If required more files then 2 can be used



Auto-provisioning

The device receives an provisioning URL to download the first file.

Example provisioning file with general settings.

```
<?xml version="1.0" encoding="UTF-8"?>
<provisioning version="1.1" productID="e2">

<nvm>

            <param name="SipProvider.0.Name" value="PBX"/>

        <!-- General data of your service provider -->

            <param name="SipProvider.0.Domain" value="192.168.178.210"/>
            <param name="SipProvider.0.ProxyServerAddress" value="192.168.178.210"/>
            <param name="SipProvider.0.ProxyServerPort" value="5060"/>
            <param name="SipProvider.0.RegServerAddress" value="192.168.178.210"/>
            <param name="SipProvider.0.RegServerPort" value="5060"/>
            <param name="SipProvider.0.RegServerRefreshTimer" value="180"/>
            <param name="SipProvider.0.TransportProtocol" value="2"/>
            <param name="SipProvider.0.UseSIPS" value="0"/>
            <param name="SipProvider.0.SRTP_Enabled" value="0"/>
            <param name="SipProvider.0.AcceptNonSRTPCalls" value="0"/>

</nvm>

<EXTENDED_PROFILE class="string" value="http://192.168.178.201/nestedprofile/test_second.xml"/>

</provisioning>
```

The Parameter:<EXTENDED_PROFILE class="string" value="http://192.168.178.201/nestedprofile/test_second.xml"/>

Contains the URL to the second provisioning file.

URL can contain:

- Name of the file (Example: test_second.xml)
- %MACD.xml (%MACD will be replaced with own MAC address)

Example for the second provisioning file

```
<?xml version="1.0" encoding="UTF-8"?>
<provisioning version="1.1" productID="e2">

<nvm>

        <!-- Handset 1 -->
        <oper value="029e74a599" name="add_hs">
            <param name="hs.RegStatus" value="ToReg"/>
        </oper>

            <param name="SipAccount.029e74a599.AuthName" value="1024" />
            <param name="SipAccount.029e74a599.AuthPassword" value="p?t_JrH1nz1zrNZE" />
            <param name="SipAccount.029e74a599.UserName" value="1024" />
            <param name="SipAccount.029e74a599.DisplayName" value="N670 1024" />
            <param name="SipAccount.029e74a599.ProviderId" value="0" />
            <param name="hs.029e74a599.DirectAccessDir" value="250" />
            <param name="hs.029e74a599.DECT_AC" value="0000" />
            <param name="hs.029e74a599.IntKeyDir" value="252"/>

</nvm>

<!-- If required you could add an URL to the next file
<EXTENDED_PROFILE class="string" value="http://192.168.178.201/nestedprofile/test_third.xml"/> -->

</provisioning>
```