

Firmware N510 IP PRO

Online update:

The firmware is available online. Newer firmware versions can be uploaded manually, using the URL provided in the release notes.

You can easily initiate the update via these 3 steps: -

Prerequisite: The phone is connected to the Internet.

Via the Handset:

1. Menu » Settings » System » Update Firmware
2. Enter base station system PIN (default setting: 0000)
3. Press the display key "Yes" to start the download

If your firmware is already up to date, the handset will inform you. No action is then needed.

Via the webpage:

1. Settings » Management » Firmware update

Manual update:

Via the webpage:

1. Settings » Management » Firmware update
2. Enter the URL for the new firmware in the **User defined firmware file:** field
3. Click on the button: **Update firmware**

Network	Firmware Update
Telephony	Data server: <input type="text" value="profile.gigaset.net/device"/>
Messaging	User defined firmware file: <input type="text"/>
Info Services	Automatic check for software updates: <input checked="" type="radio"/> Yes <input type="radio"/> No
Directories	On starting the firmware update, the device checks if the requirements of a successful firmware download are fulfilled. The firmware is then downloaded without additional feedback. During the download and update, the handset / base connection is lost. A successful update results in the handset re-establishing the base connection.
Management	<input type="button" value="Update firmware"/>
Date & Time	
Local Settings	
Miscellaneous	
Reboot & Reset	
Save & Restore	
Firmware Update	

Behind the Gigaset T500/T300 using special module to update firmware files.

A special module is made that download the files automatically from our Gigaset server and places the new files on the PBX, [click here](#).



Software version 250

Download



Software version 248

Download



Software version 247

Download



Software version 245

Download