

# FAQ Maxwell - Dialling Plans

## Introduction

You can define your own dialling plans in the **Dialling plans** area on the Web page: **Settings - Telephony - Dialling Plans**

Valid for Maxwell			
Basic	2	3	4

You can specify the following Dialling Plans:

- You can define a connection for specific phone numbers, which is always to be used to dial these numbers.
- Define if the number is to be dialed with the area code.

**i** If dialling plans overlap, the one with the greatest concordance will apply.

### Example:

There is a dialling plan for the number "02" and the one for number "023". If you dial "0231.." the second plan will apply, if you dial "0208..." the first plan will apply.

The screenshot shows the Gigaset web interface. The left sidebar has 'SETTINGS' and 'STATUS' tabs. Under 'Telephony', 'Dialling Plans' is selected. The main content area shows a table of existing dialling plans and a form to add a new one.

Phone number	Use area code	Connection	Comment	Active
85	<input checked="" type="checkbox"/>	IP 1	Bocholt Office	<input checked="" type="checkbox"/>

Form fields for adding a new plan:

- Phone number:
- Use area code:
- Connection:
- Comment:
- Active:

[+ Add](#)

## Example

### Area Code

	Country	Germany		
	International	Prefix	00	
		Area Code	49	
	Local	Prefix	0	
		Area Code	287191	

### Dialling Plans

Phone number	Use area code	Connection	Comment	Number	Outgoing INVITE
89		IP 1	Bocholt Office	89999	004928719189999 via IP 1
86		IP 1	Bocholt Local	86000	86000 via IP 1
87		IP 2	Test	87000	87000 via IP 2
891		IP 2	Test2	89199	004928719189199 via IP 2

## Auto provisioning

Parameter name	Description
Telephony.DiallingPlans.List.0-19.Number	
Telephony.DiallingPlans.List.0-19.UseAreaCode	0 = Disabled 1 = Enabled
Telephony.DiallingPlans.List.0-19.Connection	
Telephony.DiallingPlans.List.0-19.Comment	
Telephony.DiallingPlans.List.0-19.Active	0 = Disabled 1 = Enabled
Telephony.CallBarring.List.0-19.Number	
Telephony.CallBarring.List.0-19.Comment	
Telephony.CallBarring.List.0-19.Blocked	0 = Disabled 1 = Enabled
Example:	
<pre>&lt;param name="Telephony.DiallingPlans.List.0.Active" value="0"/&gt; &lt;param name="Telephony.DiallingPlans.List.0.Comment" value=""/&gt; &lt;param name="Telephony.DiallingPlans.List.0.Connection" value="0"/&gt; &lt;param name="Telephony.DiallingPlans.List.0.Number" value=""/&gt; &lt;param name="Telephony.DiallingPlans.List.0.UseAreaCode" value="0"/&gt;</pre>	