

FAQ Nx70 - Auto provisioning: Hide pages

Valid for:	N670	N870
------------	-------------	-------------

Introduction

Via provisioning it is possible to hide some web-pages. (Available in software 2.33 or higher)

Supported pages:

- Provider or PBX profiles
 - Complete menu item
 - Section: General data of your service provider
- Mobile devices
 - Administration section: Personal provider data
- Telephony
 - VoIP
 - XSI Services
- Online directories
 - Central phonebook
- Online services
 - XHTML
- System
 - Web configurator
 - Provisioning and configuration
 - Firmware

Provisioning template

```
<?xml version='1.0' encoding='utf-8'?>
<provisioning version="1.1" productID="e2">

<nvm>

  <oper name="set_webui_visibility">

    <!-- hide firmware page -->
    <param name="menu.settings/system/firmware" value="hidden" />

    <!-- show firmware page
    <param name="menu.settings/system/firmware" value="visible" /> -->

    <!-- hide Central phonebook page -->
    <param name="menu.settings/online-directories/central-phonebook" value="hidden" />

    <!-- hide XHTML page -->
    <param name="menu.settings/online-services/xhtml" value="hidden" />

    <!-- hide Provider or PBX profiles page -->
    <param name="menu.settings/provider-or-pbx-profiles" value="hidden" />

    <!-- hide Provisioning and configuration page -->
    <param name="menu.settings/system/provisioning-and-configuration" value="hidden" />

    <!-- hide Web configurator page -->
    <param name="menu.settings/system/web-configurator" value="hidden" />

    <!-- hide VOIP page -->
    <param name="menu.settings/telephony/voip" value="hidden" />

    <!-- hide XSI Services page -->
    <param name="menu.settings/telephony/xsi-services" value="hidden" />

    <!-- hide General data of your service provider section in PBX page -->
    <param name="section.general-data-of-your-service-provider-section" value="hidden" />

    <!-- hide Personal provider data section in handset page -->
    <param name="section.handset-personal-provider-data-section" value="hidden" />

  </oper>

</nvm>
</provisioning>
```