

FAQ Nx70 - Call Reject response

Introduction

Every incoming call can be rejected by the user via the **Left Soft Key** under the display "**Reject**"

The device will send an "SIP 603 decline" response message.

If required, the response can be changed via auto-provisioning to:

- 486 Busy
- 603 Decline

Valid for:	
N670	N870

Auto provisioning

Parameter	Description
SipProvider.x.DeclineResponse	603 = 603 Decline (Default) 486 = 486 Busy

Example:

```
<param name="SipProvider.0.DeclineResponse" value="603"/>
```