

FAQ Nx70 - User agent

Introduction

See below for an user-agent example.

This is seen in:

1. SIP messages
2. HTTP(s) messages

Valid for:	
N670	N870

Device	User-Agent:
N870	Gigaset N870 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX
N870E	Gigaset N870E IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX
N670	Gigaset N670 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX

From software 2.26 we have added capacity information to the HTTP(s) user agent only.

Platforms that do auto-provisioning can use this information to block the administrator to add more handsets then supported by the system.

Device			User-Agent:	
N870	Single Cell / Small		User-Agent: Gigaset N870 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=50	
	Medium		User-Agent: Gigaset N870 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=250	
	Embedded Integrator	0 DM		User-Agent: Gigaset N870 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=0
		1 DM		User-Agent: Gigaset N870 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=250
		2 DM		User-Agent: Gigaset N870 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=500
	
N870 E	Same like N870 (Above) but with "E"		User-Agent: Gigaset N870E IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=250	
N670	Single Cell		User-Agent: Gigaset N670 IP PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=20	
N870	Virtual Integrator	0 DM	User-Agent: Gigaset N870 VI PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=0	
		1 DM	User-Agent: Gigaset N870 VI PRO/83.V2.43.0+build.5f0a106;7C2F80XXXXXX;Handset=250	
		