

FAQ SL800H / S700H / R700H - Sound profiles

Introduction

The telephone has sound profiles for adapting the handset to the environment conditions:

- **Profile Loud**
- **Profile Silent**
- **Profile Personal**

You can use the **Do not disturb** profile to prevent the handset signaling an incoming call.

1. Press the Profile key  ... The profile currently set is shown
2. Switch between the profiles using the key 

Default setting		Profile Loud	Profile Silent	Profile Personal
Silent alert		On	Same as Profile Personal	Off
Ringtone		On	Off	On
Ringtone volume	Internal	5	Off	5
	External	5	Off	5
Handset volume	Receiver	5	3	3
	Handsfree	5	3	3
Advisory tones	Key click	Yes	No	Yes
	Battery tone	Yes	Yes	Yes
	Confirmation tone	Yes	No	Yes

Auto-provisioning

Via auto-provisioning, the Sound profile selection can be switched off.

Parameter	Value	Description
audio_profile_visible	• 0 or 'false' - deactivate • 1 or 'true' - activate	When deactivated, the key  has no functionality
do_not_disturb_visible	• 0 or 'false' - hide feature • 1 or 'true' - show feature	Hide/show the Do not disturb profile
do_not_disturb_active	• 0 or 'false' - DND disabled • 1 or 'true' - DND enabled	Enable or disable Do not disturb on the handset

Example:

```
<?xml version="1.0" encoding="UTF-8"?>
<provisioning version="1.1" productID="Gsdecthx">
<nvm>

    <param name="audio_profile_visible" value="1" />
    <param name="do_not_disturb_visible" value="1" />

</nvm >
</provisioning>
```