

# FAQ T640 T440 User interface

## Introduction

Your Gigaset T640/T440 comes with a Web user interface and can be configured using a browser on any computer in your local network. Via the interface you can make calls, make settings for your phone, access the call list, voicemails, the personal phone book of the extension and the company phone book.



Access to functions of the user interface can be restricted by the administrator by assigning rights to specific users or user groups. Therefore you may find that not all functions described in this guide are available to you.

## Logging on

To log on to the user interface, you need the IP address of the PBX and a user name with password.



The user name and password (PIN) are linked to the extension. If you use more than one phone (e.g. a desktop phone and a DECT handset), you will have more than one extension and a separate user name for each one. You make settings for each of your phones via the user name of the respective extension. Data that you use for all of them, e.g. your personal phone book, can be synchronised via an import/export function.

- Open a standard Web browser on your computer.
- In the address field enter the IP address of the device, e.g. `http://192.168.0.50` . . . The Login screen is displayed.
- Enter the user name (**Username**) and corresponding **PIN** -> Click **Login** . . . The user interface start screen (**Home**) opens



To change the password: -> **Personal profile**,

The screenshot displays the Gigaset user interface. At the top right is the 'Gigaset' logo. Below it, there are navigation links: 'Home' (with a house icon) and 'Menu' (with a hamburger icon). On the far right, there is a 'Profile' link with a user icon. The main content area is divided into two sections: 'Call List' on the left and 'Voicemail' on the right. The 'Call List' section shows a list of recent calls with columns for a contact icon, name, extension number, and time. The 'Voicemail' section shows a single voicemail entry with a contact icon, name, extension number, and time. Below the 'Voicemail' section, there are several settings with toggle switches: 'Do not disturb', 'Call forward', 'Hide number', and 'Call waiting'. At the bottom, there is a 'Night answer service' dropdown menu.

Contact	Extension	Time
Office mobile	216	2014-19-12 11:36 AM
Office mobile	216	2014-19-12 11:35 AM
Office mobile	216	2014-19-12 11:16 AM
M. Office	216	2014-19-12 08:31 AM
M. 217	217	2014-19-12 08:30 AM
M. 217	217	2014-19-12 08:30 AM
Office mobile	211	2014-18-12 04:02 PM

Contact	Extension	Time
Office mobile	206	2014-15-12 09:55 AM

Settings:


- Do not disturb: OFF
- Call forward: OFF
- Hide number: OFF
- Call waiting: OFF
- Night answer service: -

# Logging off

To log off from the user interface:

- **Select Profile**
- **Logout**

# Making a call

- Enter the phone number in the input field
- Click on 

or

- Enter the first character(s) of a name (first name or last name) contained in one of the contact lists ( **Internal**, **Global** oder **Private**) in the input field . . . all contacts that match the input are shown with their phone numbers.
- Click on the desired number.
- The number is displayed in a window
- Click **Start call on phone**.
- Pick up the handset of your phone or press the handsfree key . . .
- The call is started.

- [Introduction](#)
- [Logging on](#)
- [Logging off](#)
- [Making a call](#)